


The V!NE Outdoor Light is the perfect solution for outdoor event notification applications. The light is powered using CAT6 ethernet cable through the V!NE Controller. The V!NE Outdoor Light can only be used with a V!NE Controller, and may not be plugged directly into a PoE+ switch (V!NE systems should not be used with standard PoE switches). The V!NE Outdoor Light can be placed in any outdoor environment where people may need to be notified of events and is IP65 rated. Distinct pre-set color options can be pre-programmed into the V!NE system for each alert type. Custom alerts can be created based on the user's needs. The V!NE Outdoor Light features a sounder that chirps when alerts are triggered. The V!NE Outdoor Light can be placed up to 328ft away from a V!NE Controller.


## **Highlights**

- Powered using CAT6
- RGB (up to 6 distinct colors and alternating colors available)
- Volume-adjustable sounder
- Easy to install
- Lightweight

- Self-Test Functionality
- **Energy Efficient**
- Mating IP-rated connector included (cannot use standard RJ connector)
- Must not be installed with other lights on the same V!NE controller

## **Basic Dimensions (inches)**







## **Basic System Diagram**



## Table of properties (electrical, mechanical, etc.)

Physical Specifications	
Dimensions (W x D x H)	8.4in. x 7.8in. x 5.9in.
Weight	3.24 lbs.
General Information	
Patent Number	10,701,785
Warranty and Support	
Hardware	12-month
Manufacturer Part Number*	*Ordering part number may vary
19A100105	V!NE Outdoor Light